



## HP Cluster Configuration Support Matrix

For Microsoft Windows 2000 Advanced Server & HP ProLiant DL380 Packaged Cluster with MSA500

Config	Supported Servers	Server Software	Host Bus Adapters (HBAs)	Multipath Software	Storage Information	Other
#1 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2  ProLiant: • DL380 G4 or • DL380 G3*  *Note: must use the Smart Array 642 controller.	<a href="#">SmartStart</a> Ver: 7.1 utilized with PSP 7.10A	<a href="#">Smart Array 642</a> Driver: 5.62.0.32 FW: 2.26  <a href="#">Smart Array 6i</a> Driver: 5.62.0.32 FW: 2.26	<a href="#">Smart Array Multipath Software</a> Ver: 2.0b	<a href="#">StorageWorks MSA500 G2</a> Storage Controller FW: 1.40  Storage EMU FW: 2.28 on 2-port 2.30 on 4-port  Array Configuration Utility Ver: 7.15.19.0	<a href="#">Product Page</a>  <a href="#">Supporting Documentation</a>  <a href="#">MSCS Support Matrix - Archive</a>  September 2004
#2 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2  ProLiant: • DL380 G3	<a href="#">SmartStart</a> Ver: 7.0 utilized with PSP 7.00A	<a href="#">Smart Array 642</a> Driver: 5.50.0.32 FW: 1.92	<a href="#">Smart Array Multipath Software</a> Ver: 2.0a	<a href="#">StorageWorks MSA500 G2</a> Storage Controller FW: 1.14  Storage EMU FW: 1.92 on 2-port and 4-port modules  Array Configuration Utility Ver: 7.10.5.0	<a href="#">Product Page</a>  <a href="#">Supporting Documentation</a>  <a href="#">MSCS Support Matrix - Archive</a>  May 2004
#3 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2  ProLiant: • DL380 G2 or • DL380 G3	<a href="#">SmartStart</a> Ver: 6.4 utilized with PSP 6.40a	<a href="#">Smart Array 5i</a> Driver: 5.46.2.32 FW: 2.56  <a href="#">Smart Array 5i Plus</a> Driver: 5.46.2.32 FW: 2.56  <a href="#">Smart Array 532</a> Driver: 5.46.2.32 FW: 2.56	<a href="#">Smart Array Multipath Software</a> Ver: 2.0	<a href="#">StorageWorks MSA500</a> Storage Controller FW: 1.80  Storage EMU FW: 1.86 on 2-port module 1.88 on 4-port module  Array Configuration Utility Ver: 6.40.11.0	<a href="#">Product Page</a>  <a href="#">Supporting Documentation</a>  <a href="#">MSCS Support Matrix - Archive</a>  December 2003
#4 Windows 2000 Advanced Server Service Pack 4	Max supported nodes = 2  ProLiant: • DL380 G2 or • DL380 G3	<a href="#">SmartStart</a> Ver: 6.4 utilized with PSP 6.40a	<a href="#">Smart Array 5i</a> Driver: 5.46.2.32 FW: 2.38  <a href="#">Smart Array 5i Plus</a> Driver: 5.46.2.32 FW: 2.38  <a href="#">Smart Array 532</a> Driver: 5.46.2.32 FW: 2.38	N/A	<a href="#">Smart Array Cluster Storage</a> Storage Controller FW: 1.70  Storage EMU FW: 1.86 on 2-port module 1.88 on 4-port module  Array Configuration Utility Ver: 6.40.11.0	<a href="#">Product Page</a>  <a href="#">Supporting Documentation</a>  <a href="#">MSCS Support Matrix - Archive</a>  June 2003