



**TX2300 Bios Version 2.5.0.3122  
Setting up and creating an array!**

**\*Note before moving your boot device to promise controller make sure you place card in system alone with nothing attach boot to windows load drivers then you can do the following,**

**If your Disk has data on it, it will make your disk a JBOD if you want to keep the data then you must make sure your using bios version 2.5.0.3122 and then follow these steps:**

- 1.) Delete JBOD array (Press Ctrl-Y to delete the data in the disk! Or press any other key to abort) this message is cosmetic.**
- 2.) Then move to define array menu press enter then change to desired raid mode hit space bar to change raid mode: (Raid 1=Mirror) (Raid 0=Stripe) (JBOD=just a bunch of disk) then Make sure you TURN OFF Fast Init the assign disk to the Array by placing Y next to each drive.**
- 3.) Then Ctrl-Y to save then a message should pop-up that says**

**Do you want the disk image to be  
duplicated to another or do a quick  
initialize or create only? (Y/N)  
Y - Create and Duplicate  
N - Create Only**

- 4.) Press Y then select source press enter:**

**Start to duplicate the image...  
Do you want to continue? (Yes/No)  
Y - Continue, N - Abort**

**The a box should appear**

**Please Wait. . . . .  
Duplicating The image 3 % Complete**

**At this time all you have to do is wait for the image to duplicate and then reboot making sure check boot sequence so that it is booting from the Promise card.**